INSTRUCTION MANUAL FRG-7

TABLE OF CONTENTS

GENERAL DESCRIPTION 1 SPECIFICATION 2 INSTALLATION 3 CONTROLS AND SWITCHES 4 OPERATION 7 BLOCK DIAGRAM 8	
INSTALLATION	
CONTROLS AND SWITCHES	
OPERATION	
BLOCK DIAGRAM 8	
CIRCUIT DESCRIPTION9	
ALIGNMENT AND MAINTENANCE 11	
VOLTAGE CHART	
PARTS LIST14	

"WARNING: TO PREVENT FIRE OR SHOCK HAZARD, DO NOT EXPOSE THIS APPLIANCE TO RAIN OR MOISTURE."

COMMUNICATIONS RECEIVER FRG-7



GENERAL DESCRIPTION

The model FRG-7 is an all solid state synthesized communication receiver designed to cover the entire high frequency spectrum, 500 kHz to 29.9 MHz.

FRG-7 is a triple conversion super heterodyne receiver utilizing synthesized heterodyne oscillator known as the "Wadley Loop System" which offers unparalleled stable performance.

The calibrated dial mechanism provides 10 kHz frequency readout throughout the receiver coverage.

Good selectivity is provided for SSB, AM and CW with the utilization of a ceramic filter in the 455 kHz IF circuits.

The FRG-7 includes three step front end attenuator, amplified AGC and low-normal-high tone select switch for extreme flexibility that even the most demanding amateur, CBer, or broadcast listener desires. In addition, the large cabinet and hi-fi speaker will provide you with high quality audio output.

The FRG-7 includes a self-contained three way power supply for 100/110/117/200/220/234 volts AC 50/60 Hz, an internal battery or external 12 volt DC. If the AC power source fails, the unit switches automatically to an internal battery

To save battery consumption, the dial lamps can be switched off.

SPECIFICATIONS

Frequency Range:

 $0.5 \text{ MHz} \sim 29.9 \text{ MHz}$

Type of Emission:

AM, SSB (USB or LSB), CW

Sensitivity:

SSB/CW: Better than 0.7 μ V at S/N 10 dB AM : Better than 2 μ V at S/N 10 dB

Selectivity:

 ± 3 kHz at -6 dB, ± 7 kHz at -50 dB

Stability:

Less than ± 500 Hz at any 30 minutes after warm up

Antenna Impedance:

High impedance for 0.5 MHz \sim 1.6 MHz 50 ohm unbalanced for 1.6 MHz \sim 29.9 MHz

Speaker Impedance:

4 ohms

Audio Output:

2 watts

Power Requirement:

100/110/117/200/220/234 volts AC 50/60 Hz, 12 volts DC external or internal dry cell

UM-1 x 8

Power Consumption:

AC 14VA

Size:

340 (W), 153 (H), 285 (D) mm

Weight:

Approx. 7 kg without batteries

SEMICONDUCTORS COMPLEMENTS

IC:	AN-214	1	SN76514	1
FET	·:			
	3SK-40	3	2SK19	6
Tran	nsistor:			
	2SC372	8	2SC784	4
	2SD313	1		
Dio	de:			
	1N60AM	9	1S1555	2
	V06B	3		
Zon	er Diode:			
Zen				
	WZ-110	1	BZ091	1

INSTALLATION

Carefully remove the FRG-7 receiver from the carton and examine it for any physical damage.

Should any be apparent immediately notify the carrier stating the damage in detail. Save the carton and packing materials for future use.

Location:

In general, the location of the FRG-7 is not critical, however, it is recommended that excessively warm location be avoided.

POWER REQUIREMENT

The FRG-7 is supplied with a multi-voltage power transformer (export model only) and can be operated in many areas of the world where supply voltage may differ from your local supply voltage. Therefore before connecting the AC cord to the power outlet, be sure that the voltage marked on the rear of the receiver agrees with the local AC supply voltage.

CAUTION

PERMANENT DAMAGE WILL RESULT IF IMPROPER AC SUPPLY VOLTAGE IS APPLIED TO THE RECEIVER.

The FRG-7 will operate satisfactorily from any 12 volt, negative ground battery source by connecting the DC power cord (plug is supplied) to the rear panel receptacle. When making connections to the battery, be certain that the inner conductor is connected to the positive (+) and the outer conductor is connected to the negative (-) terminals of the battery. Reversed connection could permanently damage the receiver circuit.

The FRG-7 will also operate from eight dry cells in the built-in dry cell pack. (Cells are not supplied.) If the AC supply fails, the dry cell supply is automatically connected to the circuit.

The following Table 1 shows the power supply combination of FRG-7.

Power Source	1	2	3	4	5	6	7
AC Supply	0	-	_	0	0	0	_
External DC		0	_	X	_	X	0
Internal DC	_	_	0	_	X	X	X

- O Power source in use
- X Power source connected but not in use
- Power source not connected

Table 1

ANTENNA AND GROUND

The antenna is the most important part of the communication receiver installation. The FRG-7 is designed for use with a long wire antenna for $0.5 \sim 1.6 \, \text{MHz}$ and with a resonant antenna at the operating frequency having an impedance of 50 to 75 ohms for higher frequency than 1.6 MHz. This requirement is easily met by using a center fed dipole antenna resonated to the receiving frequency and fed with coaxial cable.

The FRG-7 should be connected to a good ground. The ground lead should be connected to the terminal marked E located on the rear panel of the receiver.





Fig.1 Transformer Primary Wiring

CONTROLS AND SWITCHES

The FRG-7 has been designed for ease of operation. All controls have been properly adjusted at the factory. Several panel controls and switches are unusual in operation, and an improper setting may result in poor reception. The function of various controls and switches is described in the following paragraph.

Be certain that you thoroughly understand the individual function of each before operating the receiver.



FRONT PANEL

(1) BAND

The BAND switch is a four position switch. The switch selects the desired frequency range.

(2) ATT (NOR, DX, LOCAL)

The ATT (attenuator) switch attenuates the incoming signal to prevent over-loading of the front end when an extremely strong signal is present. At the switch NOR (normal) position, the attenuator is removed from the input circuit.

(3) TONE (NOR, NARROW, LOW)

The TONE switch changes audio response of the receiver. The audio amplifier passes at the NOR position, 250 Hz through 3000 Hz, at NARROW 400 Hz through 2500 Hz and at LOW 250 Hz through 1500 Hz.

(4) (5) TUNING DIAL

The main TUNING knob determines the frequency

in combination with the BAND switch and MHz setting.

(6) FINE TUNING

The FINE TUNING control is used for precise tuning of the received signal. The main tuning dial is calibrated to the frequency with the fine control at centre.

(7) VOLUME

The VOLUME controls the audio output level from the speaker.

(8) MODE

The MODE switch determines the appropriate detector in use. In the USB·CW position, the USB (Upper Side Band) and code signal is heard. In the LSB position, the LSB (Lower Side Band) signal is heard. In the AM position, the amplitude modulated signal is heard and the Noise Limiter is put into the circuit in the AM/ANL position.

(9) LIGHT

This switch is used to turn off the lamp so as to save the current drain when the FRG-7 is operated from internal dry cells.

(10) POWER

This switch turns off the supply voltage for both AC and DC operation.

(11) PHONES

Phone jack is provided for private listening and the speaker is disconnected when the plug is inserted in this jack.

(12) RECORD

This jack is for recording purpose and the output level is set to approximately 50 mV regardless of setting of the VOLUME control.

(13) SPEAKER

Internal Speaker.

(14) DIAL SET

Main tuning dial calibrator.

(15) **S-METER**

The S-meter indicates the relative signal strength of the received signal. It is calibrated in S-unit from S-1 to S-9 and in dB over S-9.

(16) LOCK

The LOCK lamp lights up when the synthesized heterodyne oscillator is unlocked.

(17) (18) MHz


This MHz control synthesizes heterodyne oscillator to the harmonics of 1 MHz crystal oscillator. The scale is calibrated in MHz with the frequency showing the correct setting of the heterodyne signal.

(19) (20) PRESELECT

The PRESELECTOR control tunes the receiver front end. The scale is calibrated with the frequency showing the correct setting for various bands.



Fig. 2 Headphone Connection



REAR PANEL CONNECTION

(1) EXT SP

This jack is for connection of a 4 ohm external speaker when desired. With the plug in the S jack, the internal speaker is disconnected.

(2) EXT DC

Receptacle for external 12 volts DC supply.

(3) FUSE

Fuse for AC operation. Use 0.15 amp rating fuse.

(4) AC cord

Cord for AC operation.

(5) SW2

Coaxial connector for short wave listening.

(6) SW, BC, E, MUTE

SW is long wire antenna terminal for the short wave listening.

BC is long wire antenna terminal for the broadcast band listening.

E is ground connection.

MUTE is used to disable the receiver while transmitting. Connect this terminal to ground for receiver muting.

(7)(8)

AC cord holder and the internal battery pack.




Fig.3 External Power Plug Connection

OPERATION

FREQUENCY SELECTION

The receiving frequency is selected by the combination of the MHz dial and main tuning dial settings. The MHz dial selects the band at every 1 MHz and the main tuning dial selects the frequency at 10 kHz increment from 0 to 990 kHz in the band. The combination of these controls is shown in Table 2.

AMATEUR BAND RECEPTION

SSB Voice Signal:

Most amateurs use LSB on frequencies lower than 10 MHz and USB on frequencies higher than 10 MHz.

Set the controls and switches as follows;

POWER

OFF

BAND

Desired frequency segment

ATT

NOR

TONE

NOR

VOLUME

Desired listening level

411	Frequency	PRESELECT	MHz	Main Dial	BAND	MODE
	kHz 1,910	2.0	2 1 0	9 0	BI.6~4.0	USB · CW
	3,525	3.6 3.3 5 3.0 5 90mb	4 3 2	5 2 5	BI.6~4.0	LSB
	7,050	18 41mb 49r	8 7 6	050	C4.0~II.0	LSB
Amateur	14,175	15 13 13 13 15 15 15 15 15 15 15 15 15 15 15 15 15	15 14 13	175	DII.0~29.9	USB · CW
	21,225	23 20 20 13mb	22 21 20	2 2 5	DII.0~29.9	USB · CW
	28,850	30 26 11mb	29 28 27	8 5 0	DII.0~29.9	USB · CW
	590	0.6	0	5 9 0	A0.5~1.6	AM or AM/ANL
Medium Wave	980	1.0 0.	0	9 8 0	A0.5~1.6	AM or AM/ANL
	1,170	1.2 1.0	1 0	170	A0.5~1.6	AM or AM/ANL
	2,500	2.6 2.3 Talent	3 2	5 0 0	BI.6~4.0	AM or AM/ANL
	5,000	5 4.	6 5	0 .	C4.0~II.0	AM or AM/ANL
WMA\/11A	10,000	11 10 9	11 10	0	C4.0~II.0	AM or AM/ANL
	15,000	17 15 15 b 19mb	16 15 14	0	DII.0~29.9	AM or AM/ANL
	3,925	4.0 3.6	4 3 2	9 2 5	BI.6~4.0	AM or AM/ANL
	5,980	49mb	6 5 4	980	C4.0~II.0	AM or AM/ANL
	9,715	10 + 9	9 8	7 5	C4.0~II.0	AM or AM/ANL
Short Wave	11,705	12 11 11 25mb	12 11 10	7 0 5	DII.0~29.9	AM or AM/ANL
	15,120	17 15 15 mb 19mb	16 15 14	120	DII.0~29.9	AM or AM/ANL
	17,880	20 17 16mb	18 17 16	8 8 0	DII.0~29.9	AM or AM/ANL
	21,550	23 20 20 13mb	22 21 20	5 5 0	DII.0~29.9	AM or AM/ANL

Table. 2

MODE

LSB for 160, 80 and 40 meter

bands

USB for 20, 15 and 10 meter bands

DIAL SET

Center

Desired frequency. Refer to Table 2. PRESELECT

MHZ MAIN DIAL

Turn the POWER switch on. Precisely adjust the MHz dial until the LOCK lamp turns off. Tune the main tuning dial for the desired signal until the signal is clearly heard. Use the FINE TUNING control for precise tuning. When the received signal is garbled, try the opposite sideband. When an extremely strong signal is distorted, peak the PRESELECTOR for a maximum S-meter reading.

Set the ATT switch to LOCAL position to avoid front end over loading. Set the VOLUME for desired listening level.

The amateur SSB signals cut high and low audio response, so that it may be helpful to reduce the interference by setting the TONE switch at NAR-ROW or LOW position.

CW (Morse Code Signal):

The code signal can be heard with the MODE switch at USB/CW position and by tuning the main tuning dial for a desired listening tone.

BROADCAST RECEPTION

The broadcast signal is transmitted on AM mode. If impulse type noise is experienced, set the MODE switch to AM/ANL position to reduce the noise interference.




Fig.4 BLOCK DIAGRAM

CIRCUIT DESCRIPTION

The block diagram will provide you with a better understanding of this receiver. In general, the FRG-7 is a tripple conversion super heterodyne receiver utilizing synthesized local oscillator for both the first and second mixers for drift free VFO operation.

The signal from the antenna is fed through the attenuator to the gate of the FET RF amplifier Q_{101} , 3SK40. The amplified signal is fed through a low pass filter (cut off frequency 35 MHz) to the first balanced mixer consisting of Q_{102} and Q_{103} , 2SK19, where the incoming signal is mixed with a signal from the heterodyne oscillator. The first heterodyne oscillator Q_{201} , 2SC784, oscillates the signal which varies between 55.5 and 84.5 MHz.

The product of the first mixer becomes the first IF signal of 54.5 through 55.5 MHz. The first IF signal is amplified by the first IF passband amplifier Q_{104} and fed to the gate of the second mixer Q_{105} , 2SK19GR, where the first IF signal is mixed with 52.5 MHz signal. The second mixer converts the first IF signal into the second IF signal of 2.0 through 3.0 MHz.

Synthesizer oscillator Q_{301} , 2SC372, oscillates crystal controlled 1 MHz signal. The 1 MHz signal is then fed to the harmonic generator D_{301} and D_{302} , 1N60, which produces 3 to 32 MHz harmonics from the 1 MHz crystal controlled signal. The harmonic signal is fed to the dual balanced pre-mixer Q_{106} , SN76514, where the harmonics are mixed with the signal from the first heterodyne oscillator Q_{201} . The output signal from the pre-mixer passes through the selective amplifier Q_{107} , Q_{108} and Q_{109} , 2SC784, which eliminates other signals except the 52.5 MHz second heterodyne signal.

A part of the output from the selective amplifier is rectified by the detectors D_1 and D_2 , 1S1555, and the DC output voltage is amplified by the DC amplifier Q_{110} , 2SC372, and then fed to the LOCK lamp driver Q_{111} , 2SC372, which turns the LOCK lamp on when the synthesizer is unlocked.

The output signal from the first IF amplifier Q_{104} is fed to the second mixer Q_{105} , 2SK19, where the

incoming signal is mixed with the 52.5 MHz signal from the selective amplifier. The output of the second mixer becomes second IF signal of 2.0 through 3.0 MHz. The 2.0 to 3.0 MHz IF signal is then amplified by the second IF amplifier Q₄₀₁, 3SK40, and then fed to the third mixer Q_{402} , 2SK19. The third mixer converts the second IF signal into 455 kHz third IF signal. The VFO (main tuning) signal, which varies between 2,455 kHz and 3,455 kHz, is generated by the variable frequency oscillator Q_{403} , 2SC372, and supplied to the third mixer through the buffer amplifier Q_{404} , 2SK19. The 455 kHz IF signal from the third mixer is fed to the ceramic filter which is tuned to 455 kHz and has ±3 kHz passband response to eliminate interference.

The signal is then amplified by the third amplifier Q_{405} and Q_{406} , 2SC372, and fed to the appropriate detector. The AM signal is detected by balanced diode detector D_{402} , 1N60AM.

The balanced demodulator D_{403} through D_{406} , 1N60AM, is used for the detection of SSB and CW signals. The carrier signal for SSB and the beat frequency signal for CW which is generated by the BFO oscillator Q_{408} , 2SK19, are fed to the balanced demodulator through buffer amplifier, Q_{409} , 2SC372. The MODE switch shifts the BFO frequency 3 kHz lower than LSB position for USB and CW signal reception.

A part of the output from the last IF amplifier Q_{406} is fed to the AGC (Automatic Gain Control) rectifier D_{401} , 1N60. The rectified AGC voltage is then amplified by the AGC amplifier Q_{407} , 2SC372, and fed to the Q_{101} , Q_{401} and Q_{405} to control the gain of these stages automatically when the incoming signal strength is varied. Thus the receiver audio output is not effected by the variation of the input signal strength which may be caused by phasing. The S-meter is placed in the emitter circuit of Q_{407} , in which the emitter current changes in accordance with the incoming signal strength.


The detected audio output is fed through the MODE switch and the VOLUME control potentiometer VR_1 to the audio amplifier integrated circuit

 $Q_{410}\,,\,$ AN-214, which utilizes OTL (Output Transformer Less) circuit delivering 3 watts to the speaker.


The power supply is designed to operate from either 100/110/117/200/220/234 volt AC 50/60 Hz or 12 volt DC (negative ground). For AC operation, +13.5 volts are supplied from full wave rectifier D_{408} and D_{409} , **V06B**.

The 13.5 volts are used for audio amplifier stage.

The DC voltage in both AC or DC operation is supplied to the voltage regulator Q_{111} , 2SD313, to obtain an extremely stable 10 volt DC supply which is used by the various circuits. The 10 volt DC is further regulated by zener diode D_{413} , BZ-091, at 9 volts, and then supplied to the oscillators and harmonic generator circuits. When the AC supply fails, the DC voltage may be automatically supplied to the circuit through the diode D_{410} , V06B, which prevents the rectified DC voltage from flowing into the battery.



TOP VIEW



BOTTOM VIEW

FREQUENCY	1ST OSC	$_{(fo_1-fi_1)}^{1ST\ IF}$	REF FREQ (1MHz×n)	$\begin{array}{c} \text{2ND OSC} \\ (fo_1 - fh) \end{array}$	$\begin{array}{c} \text{2ND IF} \\ (\mathbf{fi}_1 - \mathbf{fo}_2) \end{array}$	3RD OSC	$\begin{array}{c} \text{3RD IF} \\ (\text{fo}_3 - \text{fi}_2) \end{array}$
f	fo ₁	fi 1	fh	fo ₂	fi 2	fo ₃	fi 3
500kHz	55.5MHz	55.0MHz	3MHz	52.5MHz	2,500kHz	2,955kHz	455kHz
1,500	56.5	55.0	4	n	2,500	2,955	11
2,500	57.5	55.0	5	11	2,500	2,955	11
3,500	58.5	55.0	6	11	2,500	2,955	"
4,500	59.5	55.0	7	U	2,500	2,955	
5,500	60.5	55.0	8	"	2,500	2,955	y
6,500	61.5	55.0	9	II.	2,500	2,955	u
7,500	62.5	55.0	10	- H.	2,500	2,955	11
8,500	63.5	55.0	- 11	11	2,500	2,955	"
9,500	64.5	55.0	12	11	2,500	2,955	11
10,000	65.5	55.5	13	"	3,000	3,455	11
11,000	66.5	55.5	14	"	3,000	3,455	"
12,000	67.5	55.5	15	11.	3,000	3,455	"
13,000	68.5	55.5	16	11	3,000	3,455	n
14,000	69.5	55.5	17	11	3,000	3,455	n
15,000	70.5	55.5	18	11	3,000	3,455	n
16,000	71.5	55.5	19	11	3,000	3,455	11
17,000	72.5	55.5	20	11	3,000	3,455	"
18,000	73.5	55.5	21	11	3,000	3,455	н
19,000	74.5	55.5	22	11	3,000	3,455	u
20,000	75.5	55.5	23	11:	3,000	3,455	11
21,100	76.5	55.4	24	11.	2,900	3,355	n
22,200	77.5	55.3	25	11	2,800	3,255	n
23,300	78.5	55.2	26	11	2,700	3,155	11.
24,400	79.5	55.1	27	11	2,600	3,055	11
25,500	80.5	55.0	28	н	2,500	2,955	n
26,600	81.5	54.9	29	11.	2,400	2,855	"
27,700	82.5	54.8	30	11.	2,300	2,755	n
28,800	83.5	54.7	31	n	2,200	2,655	11
29,900	84.5	54.6	32	11:	2,100	2,555	"

Table 3 Frequency Relationship

MAINTENANCE & ALIGNMENT

The FRG-7 has been carefully aligned and tested at the factory using the precise test instruments before shipment and, with normal usage, it should not require other than the usual attention given to any electronic equipment. Service or replacement of major component may require substantial realignment, however, under no circumstances, should realignment be attempted unless the operation of the receiver is fully understood and the malfunction has been fully analyzed and traced to misalignment. Service work should only be performed by experienced personnel using proper test equipment.

TEST EQUIPMENT REQUIRED

- (1) RF Signal Generator; Hewlett-Packard Model 606A or equivalent with one volt output at an impedance of 50 ohms and a frequency coverage to 30 MHz.
- (2) Vacuum Tube Volt-Ohm Meter (VTVM): Hewlett-Packard Model 401B or equivalent VTVM with RF probe workable to 60 MHz.
- (3) Sweep Generator and Oscilloscope workable to 60 MHz.
- (4) Frequency Counter; Yaesu YC-355D or equivalent workable to 60 MHz.

RF UNIT PB-1526

(1) 55 MHz Passband Circuit, $T_{105} \sim T_{108}$

Set the BAND switch to D and the MHz dial to 20 MHz position. Disconnect the antenna. Connect the sweep generator output between TP_{103} and TP_{102} (ground), and the oscilloscope input between TP_{104} and TP_{105} (ground). Set the center frequency of the sweep generator to 55 MHz and align T_{105} through T_{108} until the scope indicates the curve shown in Fig. 5. Disconnect the sweep generator and the scope.




Fig.5

(2) Balanced Mixer, VR_{101} , TC_{105}

Set the BAND switch to A and the MHz dial to 0. Disconnect the antenna, and connect its output to antenna terminal. Tune the receiver to the internal spurious signal at 910 kHz. Adjust VR_{101} and TC_{105} for minimum S-meter indication.

(3) Antenna Coil and Trimmer, $T_{101} \sim T_{104}$, $TC_{101} \sim TC_{104}$

Connect the signal generator output to the antenna terminal SW_2 and connect SW_1 and BC terminals with a copper wire.

Set the signal generator to 0.5 MHz, the BAND to A and PRESELECT to 0.5. Tune the receiver to the signal generator signal. Adjust T_{101} for maximum S-meter reading. Repeat this procedure at the frequencies shown in Table 4.


FREQ	BAND	PRESELECT	ALIGNMENT
0.5MH z	A	0.5	T101
1.6MH z	A	1.6	TC101
1.6MHz	В	1.6	T102
4.0MHz	В	4.0	TC102
4.0MHz	С	4.0	T103
11.0MHz	С	11.0	TC103
11.0MHz	D	11.0	T104
30.0MHz	D	30.0	TC104

Table 4

Disconnect the signal generator and the copper wire between SW_1 and BC.

(4) 52.5 MHz Selective Filter, $T_{109} \sim T_{116}$

Disconnect the input from the oscillator unit at TP_{101} . Connect the sweep oscillator output between TP_{107} and ground, and the scope between TP_{109} and ground. Set the center frequency of the sweep generator to 52.5 MHz. Adjust T_{109} to T_{116} until the scope screen shows the curve shown in Fig. 6.



Disconnect the sweep generator and scope and reconnect the wiring at TP_{101} . After completion of the above procedures make sure that the RF voltage between TP_{110} and ground is approximately 0.3 to 0.5 volt RMS. If not, repeat procedure.

(5) LOCK Level, VR₁₀₂

Adjust VR_{102} until the LOCK lamp turns off at any MHz setting of the MHz dial.

OSC UNIT PB-1523

(1) MHz Setting, T_{201} , TC_{201}

Connect the signal generator to antenna connector SW_2 and set its frequency to 3.5 MHz. Tune the receiver to the signal generator signal. Adjust T_{201} carefully until the LOCK lamp turns off at the center of 3 MHz scale on the MHz dial. Set the signal generator frequency to 27.5 MHz and tune the receiver to this signal. Carefully adjust TC_{201} until the LOCK lamp turns off at the center of 27 MHz scale on the MHz dial. Repeat above procedures until the LOCK lamp turns off at the center of every MHz scale, from 0 to 29 MHz. Disconnect the signal generator.

IF AF UNIT PB-1528

(1) Main Tuning Dial, T₄₀₃, TC₄₀₃

The following alignment should be done after warm-up of the receiver.

Set the dial hair line to the center of the dial window and FINE TUNING control to 12 o'clock position. When the main tuning dial is rotated until it stops over 1000 scale, ▲ mark should be within 5 m/m from the hair line.

Set the MODE switch to LSB and MHz dial to 0. Set the main tuning dial to 1000, then beat tone will be heard. Adjust T_{403} for zero beat. Set the main tuning dial to 0 and adjust TC_{403} for zero beat. Repeat above procedures until the tracking is completed.

(2) 2nd IF Tracking, TC_{401} , TC_{402} , T_{401} , T_{402}

Connect the signal generator to the antenna terminal SW_2 and set its frequency to 7.1 MHz. Tune the receiver to the signal from the signal generator. Set the output voltage from the signal generator for S-3 reading on S-meter. Adjust TC_{401} and TC_{402} for maximum S-meter reading. Set the signal generator to 7.9 MHz and tune the receiver to 7.9 MHz signal. Adjust T_{401} and T_{402} for maximum S-meter reading. Repeat these procedures until the tracking is completed.

(3) 3rd IF, T_{404} , T_{405}

Set the signal generator to 7.5 MHz and tune the receiver to this frequency. Adjust T_{404} and T_{405} for maximum S-meter reading. Adjust signal level so as not to satulate.

(4) S-meter Sensitivity, VR₄₀₁

Set the output level of the signal generator to $100 \, dB$. And tune the receiver for maximum Smeter reading. Adjust VR_{401} for Smeter full scale. Disconnect the signal generator.

(5) BFO Frequency, T_{406} , TC_{404}


Connect a frequency counter to TP_{405} . Set the MODE switch to LSB. Adjust T_{406} for 457 kHz on the frequency counter reading. Set the MODE switch to USB/CW and adjust TC_{404} for 453 kHz.

VOLTAGE CHART


		E (S)		C (D)	1	B (G)			E	(S)	С	(D)	В (G)
Q_{101}		1.5		4.2	G_1 G_2	1.5 4.0		Q ₃₀₁	(0.2		8.0	-1	1.1
Q ₁₀₂		1.6		9.0		0		Q401	1	2.0		9.0	G_1 1 G_2 2	. 6
Q_{103}		2.2		9.0		0		Q402		1.8		9.2		0
Q_{104}	7 -	0.5		9.0	G ₁ G ₂	0 4.5		Q403		1.8		3.5	2	2.1
Q_{105}		2.0		9.2		0		Q404	(0.5		7.8		0
Q_{107}		0.7		9.2		1.3		Q405	4	1.3		8.5	5	5.0
Q_{108}		1.1		9.2		1.7		Q406	1	1.4		9.1	2	2.0
Q_{109}		1.4		8.8		2.0		Q407	(0.01		8.7	0	0.3
Q_{110}		0		0.02		0.5		Q408	1	1.4		6.8		0
Q_{111}		0		9.5		0.02		Q409	2	2.2		7.0	3	3.3
Q_{201}		1.8		7.7		1.2		Q411	9	9.5	1	3.5	10	0.0
	1	2	3	4	5	6	7	8	9	10	11	12	13	1
Q ₁₀₆	0	8.2	8.2	4.2	2.6	0	0	0	2.2	4.1	4.1	4.2	7.3	(
Q.,,	6.5	0	7.8	11.0	6 5	0	6 5	1.0	12 5				-	-

BAND.....4.0~11.0 MHz.....7 MODE.....USB/CW Measured with VTVM Values are in VOLTS DO

Table 5



RF UNIT(PB-1526)



PART LIST

		IAKI		NA 101	
	MAIN CHASSIS		5	MJ-164	
PB	PRINTED CIRCUIT BOARD		6 (P-6)	# 4003A	
	A~Z) LAMP BOARD		7	SG-8050-0)7
	A~Z) SWITCH BOARD				
1560(.	$A \sim Z$) LED BOARD	E			
			F FUSE		
		*	1	0.5A	
D	LIGHT EIMITTING DIODE				
1	SL-103				
			FH FUSE	HOLDER	
			1	SN-1301	
R	RESISTOR				
	CARBON FILM				
1, 2	1/4 W	10Ω	PL PILOT	LAMP	
5, 9	1 ₄ W	68Ω	1, 2, 3, 4, 5, 8	BQ041-324	104A
3, 6, 12	2 ½ W	100Ω	6, 7	BQ154-338	311A
4	1 ₄ W	1 K Ω			
7, 11	1/4 W	3.3KΩ			
10	1/4 W	10ΚΩ		' RF UNIT	345 (** - 1 · 1 · 1
8	1/4 W	22 ΚΩ	PB PRINT	ED CIRCUIT BOAR	
	CARBON COMPOSITION		1526(A~Z)		
13	½W	56 Ω	1020(11 2)		
14	½ W	68Ω	Q IC, FE	T & TRANSISTOR	3
	/ 2 ***	0000	106	IC SN76514N	
			101, 104	FET 3SK40M	
VR	POTENTIOMETER		101, 104	FET 2SK19GR	
VR 1	EVH-BOAS 20A14	10KA	110, 111	Tr 2SC372Y	
1	EVIT-DUAS ZUA14	IUNA	107~109	Tr 2SC784R	(O)
			107 - 109	11 250/6410	(0)
_	O A DA CITOD		D DIODE		
С	CAPACITOR				
	CERAMIC DISC	OODE/CL)	101, 102	31 131333	
4	50WV	22PF(SL)	D DEC10	TOD	
3	50WV	33PF(SL)	R RESIS		
	MYLAR			CARBON FILM	1000
2	50W V	$0.02 \mu F$	132	1/4 W	100Ω
6, 7	50W V	$0.047 \mu F$	102, 103, 107, 11	11, 112 $\frac{1}{4}$ W	220Ω
1	50W V	$0.068 \mu \mathrm{F}$	115, 125, 129		
			119, 122	1/4 W	330Ω
			118, 128	1/4 W	470Ω
			104, 105	1/4 W	560Ω
VC	VARIABLE CAPACITOR		117, 120, 124	1/4 W	1 ΚΩ
1	C123A119	$300 \text{PF} \times 2$	114	1/4 W	3.3KΩ
2	C134ER20	$320 PF \times 3$	126	1/4 W	4.7KΩ
3	TSN 150S×05	5PF	136, 137	$\frac{1}{4}$ W	6.8KΩ
			130	1/4 W	8.2K Ω
PT	TRANSFORMER		127	1/4 W	15K Ω
1	52-51 (51-50)		123	1/4 W	22K Ω
7			121	$\frac{1}{4}$ W	27 ΚΩ
			109, 110	1/4 W	33K Ω
СТ	CHOKE		116	1/4 W	39K Ω
1	50-11		133	1/4 W	47 ΚΩ
			101, 106, 108, 12	13, 131, 135 ¼ W	100 ΚΩ
		ě	134	1/4 W	330 ΚΩ
M	METER		123	1/4 W	390Κ Ω
1	KM-005				
			135 CARBON	N COMPOSITION 1	/ ₈ W 100K Ω
			134		/8W 330K Ω
SP	SPEAKER			NTIOMETER	
1	SA-128	4Ω 2W	102	EVL-S3A-B13	1KB
	SA 120	100 A 11	101	EVL-S3A-B53	5KB
			101	171 COM 1000	JILD
S	SWITCH		C CAPAC	CITOR	
	ATT ESL-3037		O CAFAC	CERAMIC	
1			159	50WV	1PF(CH)
4	TONE ESL-3037	0	117, 138, 142, 14		2PF(CH)
2	BAND ESR-E264R2				3PF(CH)
3	MODE ESR-E264R2	U	106, 109, 122, 10		
5	POWER 8H2011		111, 130, 150	50WV	5PF(CH)
6	LAMP 8H2011		128, 131	50W V	10PF(CH)
_			119	50W V	15PF(CH)
d			129, 157, 158, 10		22PF(CH)
J	CONNECTOR		110	50W V	27PF(CH)
1	JSO-239		107, 108	50W V	33PF(CH)
2	SQ-2450-03		139, 143, 168	50WV	47PF(CH)
3	SG-8050-07		124	50W V	82PF(CH)
4	SG-8414		114	50 W V	100PF(SL)
	20 0111		4		

	66,167 50WV		301, 302	Ge	1N60FM
	105, 112, 113 50WV	$0.01 \mu { m F}$			
	16, 118, 120, 121, 123				
	$27, 135 \sim 137, 140$		X CRYSTAL		
	44, 145, 148, 149		301	HC-6/U	1MH
	56, 162~165,				
126, 1	$32, \sim 134$ $50 \mathrm{WV}$	$0.047 \mu F$			
			R RESISTOR		
T 0		_	305, 306	- 1/4 W	100 9
TC	TRIMMER CAPACITO		303, 304	1/4 W	220 9
101	ECV-1ZW	20×32 20PF	302	1/4 W	10Ks
102~	104 ECV-1ZW	40×32 40PF	301	1∕4 W	100Ks
					×
L	INDUCTOR		C CAPACITOR		
102	RFC	68μH			
101	LPF	# 220051	302	PED MICA 50WV	
103	Lii	# 220051		ERAMIC	180PF
104		# 220054	310		ODE/GH
104		# 220034	311	50WV	8PF(CH
			311	50WV	15PF(CH
Т	TRANSFORMER			50WV	22PF(CH
101	TRANSFORMER	# 220046	306, 309	50WV	27PF(CH
101		# 220046	308	50W V	33PF(CH
102		# 220047	305	50W V	68PF(CH
$\frac{103}{104}$		# 220048	301, 303, 304, 307	50W V	$0.01 \mu \mathrm{F}$
	116	# 220049			
105~	110	# 220050			
			L INDUCTOR		
			302	RFC	4.7μΗ
	OSC UNIT		301	RFC	1mH
PB	PRINTED CIRCUIT BO	DARD	303	LPF	# 220051
			i i i i i i i i i i i i i i i i i i i	AF UNIT	
Q	TRANSISTOR	The second secon	PB PRINTED CI		ARD
201	2SC78	4R (O)	1528 (A~Z)		
R	RESISTOR		Q IC, FET &	TRANSIST	OR
	CARBON FILM	M	410	IC	AN-214
204	1/4 W	100Ω	401	FET	3SK40M
					COTTACTO
203	1/4 W	$1 \mathbf{K} \Omega$	402, 404, 408		2SK19GR
203 202		1KΩ 4.7KΩ	402, 404, 408 403, 405~407, 409		2SK19GR 2SC372Y
202	1/4 W				2SC372Y
202	1/4 W 1/4 W	4.7ΚΩ	403, 405 ~ 407, 409		
202	1/4 W 1/4 W	4.7ΚΩ	403, 405 ~ 407, 409		2SC372Y
	1/4 W 1/4 W 1/4 W CAPACITOR	4.7ΚΩ	403, 405~407, 409 411 D DIODE		2SC372Y
202 201	LAPACITOR CERAMIC	4.7ΚΩ	403, 405~407, 409 411	Ge	2SC372Y
202 201 C	LAPACITOR CERAMIC 50WV	4.7KΩ 22KΩ 22PF(CH)	403, 405~407, 409 411 D DIODE	Ge Si	2SC372Y 2SD313
202 201 203 204	CAPACITOR CERAMIC 50WV 50WV	4.7KΩ 22KΩ	403, 405~407, 409 411 D DIODE 401~407	30.7577	2SC372Y 2SD313 1N60FM
202 201 201 203 204	CAPACITOR CERAMIC 50WV 50WV	4.7KΩ 22KΩ 22PF(CH)	403, 405~407, 409 411 D DIODE 401~407 408~410	Si	2SC372Y 2SD313 1N60FM V06B
202	CAPACITOR CERAMIC 50WV 50WV	4.7KΩ 22KΩ 22PF(CH) 33PF(CH)	D DIODE 401~407 408~410 413	Si Zener	2SC372Y 2SD313 1N60FM V06B BZ091
202 201 203 204 201, 20	1/4 W 1/4	4.7KΩ 22KΩ 22PF(CH) 33PF(CH) 0.01μF	403, 405~407, 409 411 D DIODE 401~407 408~410 413 412	Si Zener Zener	2SC372Y 2SD313 1N60FM V06B BZ091
202 201 203 204 201, 20	CAPACITOR CERAMIC 50WV 50WV 02 VARIABLE CAPACITO	4.7KΩ 22KΩ 22PF(CH) 33PF(CH) 0.01μF	403, 405~407, 409 411 D DIODE 401~407 408~410 413 412 FL CERAMIC F	Si Zener Zener	2SC372Y 2SD313 1N60FM V06B BZ091 WZ110
202 201 203 204 201, 20	1/4 W 1/4	4.7KΩ 22KΩ 22PF(CH) 33PF(CH) 0.01μF	403, 405~407, 409 411 D DIODE 401~407 408~410 413 412	Si Zener Zener	2SC372Y 2SD313 1N60FM V06B BZ091
202 201 203 204 201, 20	CAPACITOR CERAMIC 50WV 50WV 02 VARIABLE CAPACITO	4.7KΩ 22KΩ 22PF(CH) 33PF(CH) 0.01μF	403, 405~407, 409 411 D DIODE 401~407 408~410 413 412 FL CERAMIC F	Si Zener Zener	2SC372Y 2SD313 1N60FM V06B BZ091 WZ110
202 201 203 204 201, 20	CAPACITOR CERAMIC 50WV 50WV 02 VARIABLE CAPACITO	$4.7 \mathrm{K}\Omega$ $22 \mathrm{K}\Omega$ $22 \mathrm{PF}(\mathrm{CH})$ $33 \mathrm{PF}(\mathrm{CH})$ $0.01 \mu \mathrm{F}$ $0.01 \mu \mathrm{F}$	403, 405~407, 409 411 D DIODE 401~407 408~410 413 412 FL CERAMIC F	Si Zener Zener	2SC372Y 2SD313 1N60FM V06B BZ091 WZ110
202 201 201 203 204 201, 20	CAPACITOR CERAMIC 50WV 50WV 02 VARIABLE CAPACITO C521	$4.7 \mathrm{K}\Omega$ $22 \mathrm{K}\Omega$ $22 \mathrm{PF}(\mathrm{CH})$ $33 \mathrm{PF}(\mathrm{CH})$ $0.01 \mu \mathrm{F}$ $0.01 \mu \mathrm{F}$	### August 10 ### Au	Si Zener Zener	2SC372Y 2SD313 1N60FM V06B BZ091 WZ110 LFC-6
202 201 201 203 204 201, 20	CAPACITOR CERAMIC 50WV 50WV 02 VARIABLE CAPACITO C521 TRIMMER CAPACITOR	4.7KΩ 22KΩ 22PF(CH) 33PF(CH) 0.01μF OR 30PF×2	### August 10 ### Au	Si Zener Zener ILTER 455kHz	2SC372Y 2SD313 1N60FM V06B BZ091 WZ110
202 201 203 204 201, 20	CAPACITOR CERAMIC 50WV 50WV 02 VARIABLE CAPACITO C521 TRIMMER CAPACITOR	4.7KΩ 22KΩ 22PF(CH) 33PF(CH) 0.01μF OR 30PF×2	### August 10 ### Au	Si Zener Zener ILTER 455kHz	2SC372Y 2SD313 1N60FM V06B BZ091 WZ110 LFC-6
202 201 201 203 204 201, 20 7C 201	CAPACITOR CERAMIC 50WV 50WV 02 VARIABLE CAPACITO C521 TRIMMER CAPACITOR	4.7KΩ 22KΩ 22PF(CH) 33PF(CH) 0.01μF OR 30PF×2	### August 10	Si Zener Zener Zener ILTER 455kHz	2SC372Y 2SD313 1N60FM V06B BZ091 WZ110 LFC-6
202 201 203 204 201, 20 7C 201	CAPACITOR CERAMIC 50WV 50WV 02 50WV VARIABLE CAPACITO C521 TRIMMER CAPACITOR ECV-1ZW	$4.7 \text{K}\Omega$ $22 \text{K}\Omega$ 22PF (CH) 33PF (CH) $0.01 \mu \text{F}$	### August 14	Si Zener Zener Zener June 455kHz BON FILM W W W W W W W W W W W	2SC372Y 2SD313 1N60FM V06B BZ091 WZ110 LFC-6
202 201 201 203 204 201, 20 7C 201	CAPACITOR CERAMIC 50WV 50WV 02 50WV VARIABLE CAPACITOR C521 TRIMMER CAPACITOR ECV-1ZW	$4.7 \text{K}\Omega$ $22 \text{K}\Omega$ 22PF (CH) 33PF (CH) $0.01 \mu \text{F}$	### August 15	Si Zener Zener Zener January January Zener January	2SC372Y 2SD313 1N60FM V06B BZ091 WZ110 LFC-6 15Ω 33Ω 100Ω 120Ω
202 201 201 203 204 201, 20 7C 201	CAPACITOR CERAMIC 50WV 50WV 02 50WV VARIABLE CAPACITOR C521 TRIMMER CAPACITOR ECV-1ZW	$4.7 \text{K}\Omega$ $22 \text{K}\Omega$ 22PF (CH) 33PF (CH) $0.01 \mu \text{F}$	### August 10	Si Zener Zener Zener January Assume	2SC372Y 2SD313 1N60FM V06B BZ091 WZ110 LFC-6
202 201 201 203 204 201, 20 7C 201	CAPACITOR CERAMIC 50WV 50WV 02 50WV VARIABLE CAPACITOR C521 TRIMMER CAPACITOR ECV-1ZW	$4.7 \text{K}\Omega$ $22 \text{K}\Omega$ $22 \text{PF} (\text{CH})$ $33 \text{PF} (\text{CH})$ $0.01 \mu \text{F}$ PR $30 \text{PF} \times 2$ 10×32 10PF	## AUS	Si Zener Zener Zener January Assault Assumer	2SC372Y 2SD313 1N60FM V06B BZ091 WZ110 LFC-6 15Ω 33Ω 100Ω 120Ω 220Ω
202 201 203 204 201, 20 7C 201	CAPACITOR CERAMIC 50WV 50WV 02 50WV VARIABLE CAPACITOR C521 TRIMMER CAPACITOR ECV-1ZW TRANSFORMER # 22005	$4.7 \text{K}\Omega$ $22 \text{K}\Omega$ $22 \text{PF} (\text{CH})$ $33 \text{PF} (\text{CH})$ $0.01 \mu \text{F}$ PR $30 \text{PF} \times 2$ 10×32 10PF	## AUS	Si Zener Zener Zener ILTER 455kHz BON FILM 1/4 W	2SC372Y 2SD313 1N60FM V06B BZ091 WZ110 LFC-6 15Ω 33Ω 100Ω 120Ω 220Ω
202 201 203 204 201, 20 7C 201	CAPACITOR CERAMIC 50WV 50WV 02 50WV TRIMMER CAPACITOR ECV-1ZW TRANSFORMER # 22005	$4.7 \text{K}\Omega$ $22 \text{K}\Omega$ $22 \text{PF} (\text{CH})$ $33 \text{PF} (\text{CH})$ $0.01 \mu \text{F}$ PR $30 \text{PF} \times 2$ 10×32 10PF	## AUS	Si Zener Zener Zener Zener January A 55kHz BON FILM January W	2SC372Y 2SD313 1N60FM V06B BZ091 WZ110 LFC-6 15Ω 33Ω 100Ω 120Ω 220Ω 390Ω 470Ω
202 201 203 204 201, 20 7C 201	CAPACITOR CERAMIC 50WV 50WV 02 50WV TRIMMER CAPACITOR ECV-1ZW TRANSFORMER # 22009	$4.7 \text{K}\Omega$ $22 \text{K}\Omega$ $22 \text{PF} (\text{CH})$ $33 \text{PF} (\text{CH})$ $0.01 \mu \text{F}$ PR $30 \text{PF} \times 2$ 10×32 10PF	## AUS	Si Zener Zener Zener Zener January BON FILM January	2SC372Y 2SD313 1N60FM V06B BZ091 WZ110 LFC-6 15Ω 33Ω 100Ω 120Ω 220Ω 470Ω 560Ω
202 201 203 204 201, 20 VC 201	CAPACITOR CERAMIC 50WV 50WV 02 50WV TRIMMER CAPACITOR ECV-1ZW TRANSFORMER # 22009	$4.7 \text{K}\Omega$ $22 \text{K}\Omega$ $22 \text{PF} (\text{CH})$ $33 \text{PF} (\text{CH})$ $0.01 \mu \text{F}$ PR $30 \text{PF} \times 2$ 10×32 10PF	## AUS	Si Zener Zener Zener Zener January BON FILM January	2SC372Y 2SD313 1N60FM V06B BZ091 WZ110 LFC-6 15Ω 33Ω 100Ω 220Ω 220Ω 470Ω 560Ω 1KΩ
202 201 201 203 204 201, 20 VC 201 FC 201	CAPACITOR CERAMIC 50WV 50WV 02 50WV VARIABLE CAPACITOR C521 TRIMMER CAPACITOR ECV-1ZW TRANSFORMER # 22005 HG UNIT PRINTED CIRCUIT BO	$4.7 \text{K}\Omega$ $22 \text{K}\Omega$ $22 \text{PF} (\text{CH})$ $33 \text{PF} (\text{CH})$ $0.01 \mu \text{F}$ PR $30 \text{PF} \times 2$ 10×32 10PF	## August 14 ##	Si Zener Zener Zener Zener January J	2SC372Y 2SD313 1N60FM V06B BZ091 WZ110 LFC-6 15Ω 33Ω 100Ω 120Ω 220Ω 470Ω 560Ω 1KΩ 1.5KΩ
202 201 203 204 201, 20 VC 201 FC 201	CAPACITOR CERAMIC 50WV 50WV 02 50WV VARIABLE CAPACITOR C521 TRIMMER CAPACITOR ECV-1ZW TRANSFORMER # 22005 HG UNIT PRINTED CIRCUIT BO A~Z) TRANSISTOR	$4.7 \text{K}\Omega$ $22 \text{K}\Omega$ $22 \text{PF} \text{ (CH)}$ $33 \text{PF} \text{ (CH)}$ $0.01 \mu \text{F}$ OR $30 \text{PF} \times 2$ R $10 \times 32 10 \text{PF}$	## AUS	Si Zener Zener Zener Zener Zener James A 55kHz BON FILM Jaw Jaw Jaw Jaw Jaw Jaw Jaw Ja	2SC372Y 2SD313 1N60FM V06B BZ091 WZ110 LFC-6 15Ω 33Ω 100Ω 120Ω 220Ω 470Ω 560Ω 1KΩ 1.5KΩ 2.2KΩ
202 201 203 204 201, 20 VC 201 	CAPACITOR CERAMIC 50WV 50WV 02 50WV VARIABLE CAPACITOR C521 TRIMMER CAPACITOR ECV-1ZW TRANSFORMER # 22005 HG UNIT PRINTED CIRCUIT BO	$4.7 \text{K}\Omega$ $22 \text{K}\Omega$ $22 \text{PF} \text{ (CH)}$ $33 \text{PF} \text{ (CH)}$ $0.01 \mu \text{F}$ OR $30 \text{PF} \times 2$ R $10 \times 32 10 \text{PF}$	## AUS	Si Zener Zener Zener Zener Zener James A 55kHz BON FILM Jaw Jaw Jaw Jaw Jaw Jaw Jaw Ja	2SC372Y 2SD313 1N60FM V06B BZ091 WZ110 LFC-6 15Ω 33Ω 100Ω 120Ω 220Ω 390Ω 470Ω 560Ω 1KΩ 1.5KΩ 2.2KΩ 3.3KΩ
202 201 203 204 201, 20 7C 201 7C 201	CAPACITOR CERAMIC 50WV 50WV 02 50WV VARIABLE CAPACITOR C521 TRIMMER CAPACITOR ECV-1ZW TRANSFORMER # 22005 HG UNIT PRINTED CIRCUIT BO A~Z) TRANSISTOR	$4.7 \text{K}\Omega$ $22 \text{K}\Omega$ $22 \text{PF} \text{ (CH)}$ $33 \text{PF} \text{ (CH)}$ $0.01 \mu \text{F}$ OR $30 \text{PF} \times 2$ R $10 \times 32 10 \text{PF}$	## AUS	Si Zener Zener Zener Zener Zener A55kHz BON FILM 1/4 W	2SC372Y 2SD313 1N60FM V06B BZ091 WZ110 LFC-6 15Ω 33Ω 100Ω 120Ω 220Ω 470Ω 560Ω 1KΩ 1.5KΩ 2.2KΩ 3.3KΩ 3.5KΩ
202 201 203 204 201, 20 VC 201 FC 201	CAPACITOR CERAMIC 50WV 50WV 02 50WV VARIABLE CAPACITOR C521 TRIMMER CAPACITOR ECV-1ZW TRANSFORMER # 22005 HG UNIT PRINTED CIRCUIT BO A~Z) TRANSISTOR	$4.7 \text{K}\Omega$ $22 \text{K}\Omega$ $22 \text{PF} \text{ (CH)}$ $33 \text{PF} \text{ (CH)}$ $0.01 \mu \text{F}$ OR $30 \text{PF} \times 2$ R $10 \times 32 10 \text{PF}$	## AUS	Si Zener Zener Zener Zener Zener James A 55kHz BON FILM Jaw Jaw Jaw Jaw Jaw Jaw Jaw Ja	2SC372Y 2SD313 1N60FM V06B BZ091 WZ110 LFC-6 15Ω 33Ω 100Ω 120Ω 220Ω 390Ω 470Ω 560Ω 1KΩ 1.5KΩ 2.2KΩ 3.3KΩ

410, 425, 443	1/4 W	18K Ω
446	1∕4 W	22ΚΩ
409	$\frac{1}{4}$ W	33K Ω
401, 455, 456	1∕4 W	$47 \mathrm{K}\Omega$
405, 440	$\frac{1}{4}$ W	68Κ Ω
402, 408, 414, 434	$\frac{1}{4}$ W	$100 \mathrm{K}\Omega$
435	1∕4 W	$150 \mathrm{K}\Omega$
421	1/4 W	220 ΚΩ
) I		
197		
VR POTENTIO	OMETER	
401	EVL-S0A-E	32 300Ω B
101		
C CAPACITO	OR	
	IPPED MICA	
462	50W V	20PF
458	50W V	33 PF
		100PF
434	50WV	
410	50W V	120PF
435, 436	50W V	620PF
409	$50 \mathrm{WV}$	680PF
408	50W V	1000PF
	CERAMIC	
420, 424	50W V	1PF(CH)
438	50W V	10PF(CH)
	50W V	22PF (CH)
412		
459	50W V	100PF(UJ)
427, 428,	50W V	100PF(SL)
415	50W V	150PF(SL)
414	50W V	220PF(SL)
430	50W V	$0.001 \mu \mathrm{F}$
401, 402, 405~407	50W V	$0.01 \mu F$
416, 417, 422, 425, 4		0.01,21
	¥31	
439, 461	119 50WV	$0.047 \mu \mathrm{F}$
403, 404, 413, 418, 4		0.047μ F
421, 423, 429, 437, 4		
	MYLAR	
444	50WV	$0.003 \mu \mathrm{F}$
456	50W V	$0.0047 \mu F$
433	50W V	$0.01 \mu \mathrm{F}$
447, 449	50W V	0.03μF
440, 445	50W V	$0.2\mu \mathrm{F}$
	LECTROLYTIC	0.2µ1
		1 F
448	16WV	$\frac{1\mu F}{2}$
432, 457	16WV	$2.2 \mu \mathrm{F}$
453, 455	16WV	$10\mu\mathrm{F}$
442, 443	16W V	$33\mu F$
426	16W V	$47\mu F$
441, 446, 454, 463	16WV	$100\mu F$
450~452	16WV	100μF
100 402	10 44 4	1000μ1
TO TOURS	CADACITOD	
TC TRIMMER	R CAPACITOR	
100 10:	DOM:	2 22
403, 404		0×32 20PF
401, 402,	ECV-1ZW 5	0×32 50PF
L INDUCTO	R	
		4 7 11
407, 408	RFC	4.7μH
401	RFC	27μΗ
409	RFC	100μH
405	RFC	1mH
402~404, 406	RFC	3.9mH
T TRANSFO		
401	# 220060	
402	# 220061	
403	# 220062	
404, 405	R12-4097	
406	R12-4099	

